

Description

Distributed Audio Zone Player and Amplifier. Can Deliver up to RMS 48 Watts of Stereo. With Balanced Out to connect to Pre-Amplifier Booster. With Built in FM Radio Tuner, Built in SD Card Reader slot. Can Stream Digital Audio Through LAN/FTP from any PC or NAS on the Network. Advanced PA Port that can detect Audio Announcement Automatically mute current playing source, announce then switch back to the same music source again once announcement is completed. Additional RCA Stereo Input fro Direct Local Source Feed to allow local Music ports to connect direct from TV,DVD, IPod Dock or any other Source. Software Controllable and Integration Protocol





Art Speaker





Art Speaker

Application



Hotel



Home



Office





